




TZA-4000DPM is a multi – application 2-Zone PA amplifier with a rated output of 200 + 200 watts. It has a built in mp3 Player with USB / SD / MMC card reader. 6 Microphone inputs, 2 Aux inputs and a separate stereo CD input are provided. A USB control and a CD control are provided separately from the Mic and Aux level controls. This facilitates mixing of music and speech, and making announcements from a microphone by easily and quickly attenuating the CD or MP3 music.

TZA-4000DPM is a versatile amplifier, suitable for a wide variety of stereo or 2 zone applications in religious places, educational institutions, small auditoriums, music programmes and public meetings etc.

## Features

- 6 Mic & 2 Aux Inputs.
- Built-in MP3 player with USB, SD and MMC card reader. Remote control provided for ease of operation.
- Stereo/Mono switch to change ambience of MP3 music player.
- Separate USB level control & separate CD level control provided.
- LCD display provided to monitor the track played.
- 2-Zone operation facilitates connection and operation of two separate groups of speakers simultaneously.
- Line input & line output on each zone for connecting to a mixer and booster amplifier respectively. Pre-amplifier output for recording.
- Box Speaker/Driver Unit selector switch for each zone. Bass boost defeated at driver unit position for safer operation of driver units. Zone On/Off facility.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (Car Battery) if AC power fails.

## Rear Panel



## Specifications

POWER OUTPUT	300W + 300W Max., 200W + 200W RMS at 10% THD 180W + 180W RMS at 5% THD, 165W + 165W RMS at 2% THD
OUTPUT REGULATION	≤ 2 dB, no load to full load at 1kHz
INPUT CHANNELS	Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ Stereo Music Mode: L/R 200mV/100kΩ, Line L/R 1V/50kΩ
FREQUENCY RESPONSE	50-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
OUTPUT	Preamp 200mV/600Ω, Line 1V/1kΩ
SPEAKER OUTPUT	4Ω, 8Ω, 70V & 100V for each zone
DIGITAL PLAYER	MP3 Player with USB, SD and MMC Card Reader
POWER SUPPLY	AC: 220-240V 50/60Hz DC: 24V (2 × 12V Car Battery)
POWER CONSUMPTION	AC: 700VA DC: 9A
DIMENSIONS	W510 × H172 × D385 mm
WEIGHT	24.2kg

Design and Specifications are subject to change without notice owing to continuous product up-gradation. Technical specifications are subject to production tolerances.

We cannot be held responsible for printing errors, should they occur. AHUJA is a registered trademark of Ahuja Radios in India and other countries.

© Copyright Ahuja Radios, 2015. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law.

No part of this compilation may be reproduced in any manner or translated without written permission.